

Lutron Fluorescent Ballasts and LED Drivers

Family	Compatible Lamp Types and Wattages	Input Voltage	Control Options	Available Case Types	Low-end dimming level	Integral Sensor Connections
Fluorescent ballasts						
EcoSystem® H-Series ballasts 	<ul style="list-style-type: none"> T8 linear and U-bent: 17W, 25W, 32W T5 HO linear: 24W, 39W, 54W T5 linear: 14W, 21W, 28W 	<ul style="list-style-type: none"> UNV: 120V, 220/240V, 277V @ 50/60Hz 347V @ 60Hz 	EcoSystem® digital link	 M-case  G-case	0.7% for T8 1% for T5 and T5 HO	No
EcoSystem® H-Series ballasts Global models 	<ul style="list-style-type: none"> T8 linear: 36W T5 HO linear: 54W T5 linear: 14W, 28W 	<ul style="list-style-type: none"> 220–240V CE @ 50/60Hz 127–220V Imetro @ 50/60Hz 220–240V CCC @ 50/60Hz 	EcoSystem® digital link	 M-case	0.7% for T8 1% for T5 and T5 HO	No
Hi-lume® 3D ballasts 	<ul style="list-style-type: none"> T8 linear and U-bent: 17W, 25W, 32W, 40W T5 HO linear: 24W, 39W, 54W, 80W T5 linear: 14W, 21W, 28W T5 twin-tube: 36W, 40W, 50W 	<ul style="list-style-type: none"> UNV: 120V, 220/240V, 277V @ 50/60Hz 	<ul style="list-style-type: none"> EcoSystem digital link 3-wire 	 C-case  G-case	0.7% for T8 1% for T5 and T5 HO 5% for T5 twin-tube and T5 HO 80W	No
EcoSystem ballasts 	<ul style="list-style-type: none"> T8 linear and U-bent: 17W, 25W, 32W T8 linear Reduced-Wattage: 25W, 28W, 30W T5 HO linear: 24W, 39W, 54W T5 linear: 14W, 21W, 28W, 35W T5 twin-tube: 36W, 39W, 40W, 50W, 55W 	<ul style="list-style-type: none"> UNV: 120V, 220/240V, 277V @ 50/60Hz 	<ul style="list-style-type: none"> EcoSystem digital link 3-wire control Low-voltage wallbox controls occupancy and daylight sensors 	 J-case  G-case	10%	Yes
EcoSystem compact ballasts 	<ul style="list-style-type: none"> T4 4-pin quad-tube CFL: 18W, 26W T4 4-pin triple-tube CFL: 26W, 32W, 42W 	<ul style="list-style-type: none"> UNV: 120V, 220/240V, 277V @ 50/60Hz 	<ul style="list-style-type: none"> EcoSystem digital link 3-wire 	 K-case	5%	No
Hi-lume ballasts 	<ul style="list-style-type: none"> T5 HO linear: 24W, 39W, 54W T4 4-pin triple-tube CFL: 26W, 32W 	<ul style="list-style-type: none"> 120V, 277V @ 60Hz 	3-wire	 A-case  C-case	1%	No
Tu-Wire® ballasts 	<ul style="list-style-type: none"> T8 linear and U-bent: 25W, 32W T4 4-pin quad-tube CFL: 18W, 26W T4 4-pin triple-tube CFL: 18W, 26W, 32W 	<ul style="list-style-type: none"> 120V @ 60Hz 	Tu-Wire® (fluorescent)	 A-case  B-case  C-case	5%	No
LED drivers						
Hi-lume A-Series LED drivers 	<ul style="list-style-type: none"> LED light engines, up to 40W 	<ul style="list-style-type: none"> UNV: 120V, 220/240V, 277V @ 50/60Hz 120V only for forward phase control models 	<ul style="list-style-type: none"> EcoSystem digital link 3-wire Forward phase control (neutral required) 	 K-case  M-case	1%	No
EcoSystem LED drivers Global model 	<ul style="list-style-type: none"> LED light engines, up to 25W 	<ul style="list-style-type: none"> 220–240V CE @ 50/60Hz 	EcoSystem digital link	 P-case	1%	No



© 2011 Lutron Electronics Co., Inc. | P/N 368-2393 REV A

www.lutron.com/ballasts

www.lutron.com/LED

Technical Support: 1.800.523.9466... 24 hours/7days (US/CAN)

